

## EnerGenie Programmable surge protector with LAN interface

### EG-PMS-LAN

### YOUR SWITCH IS MY COMMAND

- NOW APP in APP-STORE AVAILABLE!
- Easy control of the EG-PMS-LAN with your iPhone or iPad. Search in iTunes for Powerman.
- EG-PMS-LAN is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your local network or Internet, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PMS-LAN via Internet from all over the world, even with your smartphone.
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via LAN or Internet
- Switch electric devices on or off with your smartphone, wherever you are
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals



### Features

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Because of the LAN interface and the built-in web-server, EG-PMS-LAN can be accessed from any computer within your local network (via an Internet browser or Power manager software)

### Packaging

Q'ty in crtn, pcs	10
Crtn volume, CUM	0.049538
Crtn weight, kgs	14.4
Individual package size LxWxH:	142x65x400 mm
Carton size LxWxH:	470x310x340 mm
Country of origin	CN
Barcode	8716309066686
Customs code	8536301090

### Package contents

- EG-PMS-LAN
- User manual and Quick installation guide
- RJ45 cross-over cable (red), RJ45 LAN cable (grey)
- CD with Power Manager software for Windows

### Specifications

- RJ45 LAN connector
- Input voltage: up to 250 VAC, 50 – 60 Hz
- Maximum load current: 10A
- Maximum power consumption: 25 W
- Built-in power supply
- Power cord: 18 m
- Dimensions: 378 x 100 x 57 mm
- Net weight: up to 1 kg
- Hardware schedule possibilities:
  - Maximum number of independent hardware schedules 16
  - Time interval between the events – from 1 minute to 180 days

### System requirements

- Local area network with RJ45 sockets
- Any Internet-enabled computer connected to the local area network
- Computer running Windows® 2000/XP/Vista or Windows 7 is required for using the Power Manager software (use of this software is not compulsory)

### Certificates

